



# 深圳市新佰特电子有限公司

SHENZHEN NEWBESTTOOLS ELECTRONICS CO.,LTD

地址: 广东省深圳市宝安区 31 区前进路水口花园西三巷 8 号  
电话: 0755-27851661 / 27851665 传真: 0755-27851665

邮政编码: 518133  
http://www.nbtmi.com



UT15048x48x100mm4-digit displayNumber of SP: 2

Without alarm	Without other options	UT150-RN	Relay output	
		UT150-VN	Voltage pulse output	
		UT150-AN	Current output	
With 2 alarms		With retransmission output	UT150-RN/AL	Relay output
			UT150-VN/AL	Voltage pulse output
			UT150-AN/AL	Current output
	With external contact input	UT150-RN/AL/RET	Relay output	
		UT150-VN/AL/RET	Voltage pulse output	
		UT150-AN/AL/RET	Current output	
	With communication	With external contact input	UT150-RN/AL/EX	Relay output
			UT150-VN/AL/EX	Voltage pulse output
			UT150-AN/AL/EX	Current output
With retransmission output/external contact input		UT150-RN/AL/RS	Relay output	
		UT150-VN/AL/RS	Voltage pulse output	
		UT150-AN/AL/RS	Current output	
With retransmission output/external contact input	UT150-RN/AL/RET/EX	Relay output		
	UT150-VN/AL/RET/EX	Voltage pulse output		
	UT150-AN/AL/RET/EX	Current output		

### 产品规格:

实际值/设定值显示	4 位/4 位
输入种类	1 组可选(TCs、RTDs、mV.V)
显示精度	±2℃ ±1digit for TC/±1℃ ±1digit for RTD ±0.3% ±1digit for mV/V input

13827450276

<http://www.nbtmi.com>

13556854588



# 深圳市新佰特电子有限公司

SHENZHEN NEWBESTTOOLS ELECTRONICS CO.,LTD

地址：广东省深圳市宝安区 31 区前进路水口花园西三巷 8 号  
电话：0755-27851661 / 27851665 传真：0755-27851665

邮政编码：518133  
<http://www.nbtmi.com>

取样周期	500ms
控制回路及模式	循环、自动模式
设定点数	1
控制方式	ON/OFF 时间-比例/PID, 加热/冷却
Super,自动演算	Super、自动演算
输出种类	Relay,电压, 4~20mA 可选 (SSR, SCR)
计时功能	二组计时 0~99 分 59 秒
接点输出	2 (警报或计时器输出)
RS485 通讯协议	TWO-WIRE、MODBUS、PC-Link、Ladder
认证	已通过 UL、CE、CSA 国际认证 IP65 防护盖
其它参数	外形尺寸 48×48×100mm 电源 90~260VAC 功率损耗 8VA
环境温、湿度	温度 0~50℃、湿度 20~90%RH

13827450276

<http://www.nbtmi.com>

13556854588